

STARTERKIT-UC20-WL2000-AC**Weidmüller Interface GmbH & Co. KG**

Klingenbergstraße 26

D-32758 Detmold

Germany

www.weidmueller.com**Allgemeine Bestelldaten**

Best.-Nr.	2666080000
Art	STARTERKIT-UC20-WL2000-AC
GTIN (EAN)	4050118681536
VPE	1 Stück

STARTERKIT-UC20-WL2000-AC**Weidmüller Interface GmbH & Co. KG**

Klingenbergstraße 26

D-32758 Detmold

Germany

www.weidmueller.com**Technische Daten****Abmessungen und Gewichte**

Nettogewicht	800 g
--------------	-------

Klassifikationen

ETIM 6.0	EC000236	ETIM 7.0	EC000236
ETIM 8.0	EC000236	ETIM 9.0	EC000236
ECLASS 9.0	27-24-22-07	ECLASS 9.1	27-24-22-07
ECLASS 10.0	27-24-22-07	ECLASS 11.0	27-24-22-07
ECLASS 12.0	27-24-22-07	ECLASS 13.0	27-24-22-07
ECLASS 14.0	27-24-22-07		

Umweltanforderungen

REACH SVHC	Lead 7439-92-1
SCIP	8eb7beda-d24b-434b-95c4-ddc050faf33c
RoHS-Konformitätsstatus	Konform mit Ausnahme
RoHS-Ausnahme (falls zutreffend/bekannt)	7a, 7cl

Zulassungen

ROHS	Konform
------	---------

Downloads

Engineering-Daten	CAD data – Engineering Drawing - STARTERKIT-UC20-WL2000-AC CAD data – Wiring diagram - STARTERKIT-UC20-WL2000-AC Quick start guide – Modbus - Understanding Coils and Register Quick start guide – Starter-Kit u-control Quick Start Guide for Starter-Kit Web - Three-state Temperature Controller Setup of Procon Web ES on u-OS
Software	Project Examples and Templates – Example program Project Dekora.ucp
Anwenderdokumentation	Weidmüller software license agreement V1.0 Quickstartguide for Starterkits u-control Project setup guide - u-create studio - EN Quick reference / Instruction inlay - u-control web hardware
Kataloge	Catalogues in PDF-format